

428 McCormick Street
San Leandro, CA 94577
510-567-8503
510-567-8506 [fax]
www.inexinnovation.com

Dealer and Distributor
Please Contact:
510-326-2985
jimmyko@inexinnovation.com



PRE-A200 and PRE-A202

General Specifications

| Parameter | Specification |
|--------------------------------------|---|
| Frequency Response | 4 Hz to 30 MHz |
| Maximum Output | 2.5 volts unbalanced 5.0 volts balanced |
| Sensitivity | Unbalanced Line Level Inputs 2.5 volts Balanced Inputs 5.0 volts |
| XLR Connector Pin-out (Balanced I/O) | pin 1 ground, pin 2 positive, pin 3 negative |
| Audio Signal I/O | 2 pairs of RCA inputs 2 pairs of RCA outputs 2 pairs of balanced female XLR inputs 1 pair of balanced male XLR outputs |
| Line Power | 100 - 240 VAC |
| Remote Control Battery | Two AAA |
| Dimensions L x W x H | 16.5" x 14.2" x 4.3" 420 x 360 x 110 mm |
| Weight | 16 lb / 7.3 kg |

Order Information

| Part Number | Description |
|-------------|--|
| PRE-A200 | Power up by standard INEX4000 Li-ion battery pack |
| PRE-A202 | Dual power sources with full-balanced circuit design |

The information set forth in this document reflects our best knowledge at the time of issue. The document is subject to changes pursuant to new developments and findings, and a similar reservation applies to the properties of the products described. We undertake no liability for results obtained by usage of our products and information.